



1

Attach the HINGE (PART D) to the VITAMINI WING (PART A) using the shorter METAL SCREWS (PART E) and TOOL provided. Make sure the shiny side of the WING is facing up towards you. Refer to Fig A.

NOTE: The preinstalled black screw on the HINGE can be loosened ever so slightly so the HINGE bends a little easier.



Fig. A

2

Place the U-SHAPED SPACER (PART G) over the preinstalled black screw on the HINGE and place the 2 SILVER SCREWS (PART H) through both the U-SHAPED SPACER and HINGE. You may now thread the NUTS (PART F) on the end of these SILVER SCREWS. Do not tighten, leave a small space as shown in Fig B.



Fig. B

3

Place the ACRYLIC HOLDERS (PART B) over and around the VITAMINI and thread the SILVER SCREWS (also PART B) onto the VITAMINI. Refer to Fig C.




Fig. C

4

Now slide your assembled Vitamini Holder into the side of the RAIL (not included). The best position for each holder is usually 15cm (6") away from each end of the rail. Refer to Fig D.



Fig. D



5

When the holder is in your desired position, you may lift the acrylic part of the holder and tighten the 2 silver screws. Refer to Fig E.



Fig. E

6

You may now thread the LONG PLASTIC SCREW (PART I) into the bottom of the U-SHAPED SPACER on the holder. This screw is used to adjust the angle and hold the weight of your Vitamini LED strip. Refer to Fig F.



Fig. F

7

Now you can lock your VITAMINI into the ROTATABLE HOLDER by screwing in the LARGE BLACK PLASTIC SCREWS (PART C). Refer to Fig G.



Fig G

8

